

CPA 1 and SLP-03 IR Remote Codes

October, 12, 2005

All codes - to Philips RC-5 standard

Key Printing	Function	System	Command	Notes
POWER	POWER ON / OFF	0x04	0x24	
MUTE	MUTE	0x04	0x1D	
< INPUT SELECTOR	< INPUT SELECTOR	0x04	0x31	
INPUT SELECTOR >	INPUT SELECTOR >	0x04	0x33	
- VOLUME	- VOLUME	0x04	0x0D	
VOLUME +	VOLUME +	0x04	0x2C	
< BALANCE	< BALANCE	0x04	0x3D	
BALANCE >	BALANCE >	0x04	0x38	
BRIGHT	BRIGHT	0x04	0x29	
BALANCED	BALANCED INPUT	0x04	0x12	
CD	CD INPUT	0x04	0x13	
TUNER	TUNER INPUT	0x04	0x14	
AUX 1	AUX 1 INPUT	0x04	0x15	
AUX 2	AUX 2 INPUT	0x04	0x16	
CINEMA BY PASS	CINEMA BY PASS	0x04	0x19	
TAPE MONITOR	TAPE MONITOR	0x04	0x1A	
CD PLAYER USE ONLY				
OPEN/CLOSE	OPEN/CLOSE	0x04	0x2D	
STOP	STOP	0x04	0x1F	
PAUSE	PAUSE	0x04	0x35	
PLAY	PLAY	0x04	0x2A	
SRC	SAMPLE RATE CONVERTER	0x04	0x21	
PREVIOUS	PREVIOUS	0x04	0x11	
NEXT	NEXT	0x04	0x10	
POWER	CD PLAYER POWER ON/OFF	0x04	0x0C	